

**External Dimensions** 







#### Dimensions

Fig	Fan	D1	D	H1		W1	w	Model
A	Yes	10.5(0.41)	116.5(4.59)	140(5.51)	151(5.94)	89(3.50)	100(3.94)	VFD002M11A
	Yes	10.5(0.41)	116.5(4.59)	140(5.51)	151(5.94)	89(3.50)	100(3.94)	VFD004M11A
A	Yes	10.0(0.39)	113.0(4.45)	130.5(5.14)	141.5(5.57)	74(2.91)	85(3.35)	VFD004M21A
_ ^	Yes	10.5(0.41)	116.5(4.59)	140(5.51)	151(5.94)	89(3.50)	100(3.94)	VFD004M21B
	Yes	10.0(0.39)	113.0(4.45)	130.5(5.14)	141.5(5.57)	74(2.91)	85(3.35)	VFD004M23A
	Yes	10.5(0.41)	116.5(4.59)	140(5.51)	151(5.94)	89(3.50)	100(3.94)	VFD007M11A
	Yes	10.0(0.39)	113.0(4.45)	130.5(5.14)	141.5(5.57)	74(2.91)	85(3.35)	VFD007M21A
	Yes	10.5(0.41)	116.5(4.59)	140(5.51)	151(5.94)	89(3.50)	100(3.94)	VFD007M21B
A	Yes	10.0(0.39)	113.0(4.45)	130.5(5.14)	141.5(5.57)	74(2.91)	85(3.35)	VFD007M23A
	Yes	10.5(0.41)	116.5(4.59)	140(5.51)	151(5.94)	89(3.50)	100(3.94)	VFD007M43B
	Yes	10.5(0.41)	116.5(4.59)	140(5.51)	151(5.94)	89(3.50)	100(3.94)	VFD007M53A
	Yes	10.0(0.39)	113.0(4.45)	130.5(5.14)	141.5(5.57)	74(2.91)	85(3.35)	VFD015M21A
	Yes	10.5(0.41)	116.5(4.59)	140(5.51)	151(5.94)	89(3.50)	100(3.94)	VFD015M21B
A	Yes	10.0(0.39)	113.0(4.45)	130.5(5.14)	141.5(5.57)	74(2.91)	85(3.35)	VFD015M23A
	Yes	10.5(0.41)	116.5(4.59)	140(5.51)	151(5.94)	89(3.50)	100(3.94)	VFD015M43B
	Yes	10.5(0.41)	116.5(4.59)	140(5.51)	151(5.94)	89(3.50)	100(3.94)	VFD015M53A
В	Yes	8.2(0.32)	166.3(6.55)	205(8.07)	220(8.66)	110(4.33)	125(4.92)	VFD022M21A
A	Yes	10.5(0.41)	116.5(4.59)	140(5.51)	151(5.94)	89(3.50)	100(3.94)	VFD022M23B
A	Yes	10.5(0.41)	116.5(4.59)	140(5.51)	151(5.94)	89(3.50)	100(3.94)	VFD022M43B
A	Yes	10.5(0.41)	116.5(4.59)	140(5.51)	151(5.94)	89(3.50)	100(3.94)	VFD022M53A
	Yes	8.2(0.32)	166.3(6.55)	205(8.07)	220(8.66)	110(4.33)	125(4.92)	VFD037M23A
В	Yes							VFD037M43A
	Yes							VFD037M53A
	Yes	8.2(0.32)	166.3(6.55)	205(8.07)	220(8.66)	110(4.33)	125(4.92)	VFD055M23A
В	Yes							VFD055M43A
	Yes							VFD055M53A
В	Yes	8.2(0.32)	166.3(6.55)	205(8.07)	220(8.66)	110(4.33)	125(4.92)	VFD075M43A
	Yes							VFD075M53A



### ASIA DELTA ELECTRONICS, INC. Taoyuan Plant/ 31-1. SHIEN PAN ROAD, KUEI SAN INDUSTRIAL ZONE, TAOYUAN SHIEN.

TEL: 886-3-362-6301 FAX: 886-3-362-7267 www.delta.com.tw/industrialautomatio

#### NORTH/SOUTH AMERICA DELTA PRODUCTS CORPORATION EUROPE DELTRONICS (NETHERLANDS) B.V. Sales Office/ DE WITBOGT 15 P.O. BOX 12173

NL-5652 AG EINDHOVEN 5101 DAVIS DRIVE THE NETHERLANDS RESEARCH TRIANGLE PARK, NC 27709, U.S.A. FAX: 31-40 259-2851 TEL: 1-919-767-3813 FAX: 1-919-767-3969

DELTA ELECTRONICS (JAPAN) INC. DELTA SHIBADAIMON BLDG. 2-1-14 SHIBADAIMON MINATO-KU TOKYO, 105-0012, JAPAN

FAX: 81-3-5733-1211

DELTA ELECTRONICS, INC.

**Delta VFD-M Series** 

Variable Speed AC Motor Drives

## Features:


- ► 16-bit microprocessor controlled PWM output
- ► Automatic torque boost & slip compensation
- ► Output frequency 0.1~400Hz
- ▶ 8-step speed control & 7-step process control
- ► Low-noise carrier frequency up to 15kHz
- ▶ 2 accel./decel. times & S-curve
- ► Process follower 0~10VDC, 4~20mA
- ► Communication interface RS-485 (Baud rate 38400)
- ► Energy saving & automatic voltage regulation
- ► Adjustable V/F curve & Simple vector control
- Automatic adjustment of accel./decel. times
- PID feedback control ► Simple position function
- ► 0 Speed Holding function
- Sleep / Revival function build-in

www.delta.com.tw/industrialautomation





- 1 Phase 115V Series: 0.2~0.75KW (0.25~1HP)
- 1 Phase 230V Series: 0.4~2.2KW (0.5~3HP) 3 Phase 230V Series: 0.4~5.5KW (0.5~7.5HP)
- 3 Phase 460V Series: 0.75~7.5KW (1~10HP)
















20051021AMD-ME

Standard wiring diagram



NOTE: Do not plug a Modem or telephone line to the RS-485 communication port, permanent damage may result. Terminal 1& 2 are the power sources for the optional copy keypad and should not be used while using RS-485 communication.

- \* If it is single phase model, please select any of the two input power terminals in main circuit power.
- \* Single phase model can be input 3-phase power.

### Standard specifications

### 115V Series 1-Phase

Mode Number VFD	002	004	007		
Max. Applicable Motor Output (kW)	0.2	0.4	0.75		
Max. Applicable Motor Output (HP)	0.25	0.5	1.0		
Rated Output Capacity (kVA)	0.6	1.0	1.6		
Rated Output Current (A)	1.6	2.5	4.2		
Maximum Output Voltage (V)	3-Phase proportional to twice the Input Voltage				
Output Frequency (Hz)	0.1~400Hz				
Carrier Frequency (kHz)	1-15				
	Single Phase				
Rated Input Current (A)	6	9	16		
Rated Voltage , Frequency	Single ph	ase 100-120V	50/60Hz		
Voltage Tolerance		±10%(90~132V	)		
Frequency Tolerance		± 5%(47~63Hz)	1		
Gooling Method		Fan Cooled			
Weight(Kg)	1.5	1.5	1.5		
	Max. Applicable Motor Output (kW) Max. Applicable Motor Output (HP) Rated Output Capacity (kW) Rated Output Current (A) Maximum Output Voltage (Y) Output Frequency (Hz) Carrier Frequency (kHz) Rated Input Current (A) Rated Voltage - Frequency Voltage Tolerance Frequency Tolerance Cooling Method	Max. Applicable Motor Output (kW) 0.2  Max. Applicable Motor Output (HP) 0.25  Rated Output Capacity (kW) 0.6  Rated Output Capacity (kW) 1.6  Maximum Output Voltage (V) 3-Phase propo  Output Frequency (Hz)  Carrier Frequency (Hz)  Rated Input Current (A) 6  Rated Voltage (Frequency Single proposed (Frequency Single proposed (Frequency Single proposed (Frequency Single proposed (Frequency Total Proposed (	Max. Applicable Motor Output (kW)         0.2         0.4           Max. Applicable Motor Output (HP)         0.25         0.5           Rated Output Capacity (kWa)         0.6         1.0           Rated Output Current (A)         1.6         2.5           Maximum Output Voitage (V)         3-Phase proportional to lwice it           Output Frequency (Hz)         0.1-400Hz           Carrier Frequency (Hz)         1.15           Rated Input Current (A)         6         9           Rated Voitage - Frequency         5 ingle phase 00-120V           Voltage Tolerance         ± 10%(90-132V           Frequency Tolerance         ± 5%(47-63Hz,           Cooling Method         Fan Cooled		

# Standard specifications

### 230V Series 1-Phase/3-Phase

	Model Number VFD M	004	007	015	022	037	055	
	Max. Applicable Motor Output (kW)	0.4	0.75	1.5	2.2	3.7	5.5	
	Max. Applicable Motor Output (HP)	0.5	1.0	2.0	3.0	5.0	7.5	
g.	Rated Output Capacity (kVA)	1.0	1.9	2.7	3.8	6.5	9.5	
Rating	Rated Output Current (A)	2.5	5.0	7.0	10	17	25	
#	Maximun Output Voltage (V)	3-Phase Proportional to input voltage						
Output	Output Frequency (Hz)	0.1~400Hz						
ō	Carrier Frequency (kHz) 1-15							
	Rated Input Current (A)	Single / 3-Phase 3-Phase					nase	
		6.3 / 2.9	11.5 / 7.6	15.7 / 8.8	27 / 12.5	19.6	28	
ij	Single (3-phase Input Current)	3.2	6.3	9.0	12.5			
Input Rating	Rated Voltage , Frequency	Single / 3-Phase 3-Pha 200-240V , 50 / 60Hz 200-240V , 5						
	Voltage Tolerance	± 10%(180~264V)						
	Frequency Tolerance	± 5%(47~63Hz)						
	Cooling Method			Fan C	ooled			
	Weight (Kg)	2.2 / 1.5	2.2 / 1.5	2.2 / 1.5	2.2	3.2	3.2	

### 460V Series 3-Phase

	Model Number VFD M	007 015 022		037	055	075			
	Max. Applicable Motor Output (kW)	0.75	1.5	2.2	3.7	5.5	7.5		
	Max. Applicable Motor Output (HP)	1.0	2.0	3.0	5.0	7.5	10		
9	Rated Output Capacity (kVA)	2.3	3.1	3.8	6.2	9.9	13.7		
atin	Rated Output Current (A)	3.0	4.0	5.0	8.2	13	18		
# H	Rated Output Caprenty (kVA)  Rated Output Gurent (A)  Rated Output Gurent (A)  Maximun Output Voltage (V)  Output Frequency (Hz)		3-Ph	ase Proportio	nal to input v	oltage			
효	Output Frequency (Hz)		0.1~400Hz						
ō	Carrier Frequency (kHz)	Carrier Frequency (kHz) 1-15							
		3-Phase							
ē	Rated Input Current (A)	4.2	5.7	6.0	8.5	14	23		
Input Rating	Rated Voltage, Frequency		3-F	hase 380 to	480V , 50 / 60	Hz			
Ħ	Voltage Tolerance	± 10%(342~528V)							
트	Frequency Tolerance ± 5%(47~63Hz)								
	Cooling Method			Fan C	ooled				
	Weight (Kg)	1.5	1.5	2.0	3.2	3.2	3.3		

#### 575V Series 3-Phase

	Model Number VFDM	007	015	022	037	055	075		
	Max. Applicable Motor Output (kW)	0.75	1.5	2.2	3.7	5.5	7.5		
	Max. Applicable Motor Output (HP)	1.0	2.0	3.0	5.0	7.5	10		
g.	Rated Output Capacity (kVA)	1.7	3.0	4.2	6.6	9.9	12.2		
Output Rating	Rated Output Current (A) 1.7 3.0 4.2 6.6			9.9	12.2				
¥	Maximun Output Voltage (V)	3-Phase Proportional to input voltage							
ī.	Output Frequency (Hz)	0.1~400Hz							
0	Carrier Frequency (kHz)	1-10							
6		Rated Input Current (A) 3-Phase							
Input Rating	Rated Input Current (A)	2.4	4.2	5.9	7.0	10.5	12.9		
22	Rated Voltage , Frequency		3-F	hase 500 to	600V , 50 / 60	)Hz			
ם	Voltage Tolerance	-15% , +10% ( 425~660V )							
- 1	Frequency Tolerance			± 5%(4	7~63Hz)				
	Cooling Method			Fan C	ooled				
	Weight (Kg)	1.5	1.5	2.0	3.2	3.2	3.3		

# Standard specifications

	Control System		SPWM (Sinusoidal Pulse Width Modulation)control (V/F or sensorless vector control)			
	Freq. Setting Resolution		0.1Hz			
	Output Frequency Resolution		0.1Hz			
	Torque Characteristics		Including the auto-torque, auto-slip compensation; starting torque can be 150% at 5.0Hz			
S.	Overload Endur		150% of rated current for 1 minute			
rist	Skip Frequency		Three zones, settings range 0.1-400Hz			
acte	Accel/Decel Tin	10	0.1 to 600 seconds (2 independent settings for Accel/Decel Time)			
Control Characteristics	Stall Prevention Frequency Set		20%-200%, Setting of Rated Current			
	DC Injection Braking		Operation frequency 0-60Hz, output 0-100% rated current Start time 0-5 seconds, stop time 0-25 seconds			
	Braking Torque		Approx. 20% (up to 125% possible with option braking resistor or braking unit externally mounted)			
	V/F Pattern		Adjustable V/F pattern			
	Frequency	Keypad	Set by ▲▼			
lics	Setting	External Signal	Potentiometer-5KΩ/0.5W, 0 to +10VDC; 4 to 20mA, RS-485 interface; Multi-Function Inputs 0 to 5 (7 steps, Jog, up/down)			
rist	Operation	Keypad	Set by RUN, STOP			
haracte	Setting Signal	External Signal	2 wires / 3 wires (Run, Stop, Forward / Rev, ), JOG operation, RS-485 serialinterface (MODBUS)			
Operating Characteristics	Multi-Function Input Signal		Multi-step selection 0 to 7, Jog, accelidecel inhibit, first to forth accelidecel switches, counter, PLC operation, external Base Block (NC, NO), auxiliary motor control is invalid, ACI/AVI selections, drive reset, UP/DOWN key settings, sink/source selection			
0	Multi-Function Output Indication		AC Drive Operating, Frequency Attained, Non-zero, Base Block, Fault Indication, Local/Remote indication, PLC Operation indication, Auxiliary Motor Output, Driver is Ready, Overheat, Alarm, Emergency Stop			
	Analog Output Signal		Analog frequency/current signal output.			
Alam Output Contaact			1Form C contact or open collector output.			
Operation Functions			AVR, S-Curve, Over-Voltage, Over-Current Stall Prevention, Fault Records, Adjustable Carrier Frequency, DC Braking, Momentary Power Loss restart, Auto Truinig, Frequency Limits, Parameter Lock/Reset, Veder Control, Counter, PID Control, PLC, MODBUS Communication, Reverse Inhibition, abnormal reset, abnomal re-start, digilal frequency output, sleep/revival function, 1 st/2nd frequency source selections			
Pr	otective Functions	Self-testing, Over Voltage, Over Current, Under Voltage, Overhoad, Overheating, Extended Functions  Self-testing, Over Voltage, Over Current, Under Voltage, Overhoad, Overheating, Extended Functions				
Display Keypads		Keypads  6-key, 4-digit, 7-segment LED, 4 status LEDs, master frequency, output frequency, Output current, custom units, parameter values for setup, review and faults, RIN, STOP, RESET, FWD/REV				
su	Protection Level		IP20			
Enviromental Conditions	Pollution Degree		2			
	Installation Location		Altitude 1,000m or less, keep from corrosive gas, liquid and dust			
	Ambient Tempe		-10°C to 40°C (-10°C to 50°C without blind plate) Non-Condensing and not frozen			
menta	Storage / Transportation Temperature		-20°C to 60°C			
vir	Ambient Humidity		Below 90% RH (non-condensing )			
ŭ	Vibration		9.80665m/s² (1G) less than 20Hz, 5.88m/s² (0.6G) at 20 to 50Hz			
Ap	pprovals		CE (II) us C			